


Lab - Configuring IPv6 Addresses on Network Devices

Topology



Addressing Table

Device	Interface	IPv6 Address	Prefix Length	Default Gateway
R1	G0/0	2001:DB8:ACAD:A::1	64	N/A
	G0/1	2001:DB8:ACAD:1::1	64	N/A
S1	VLAN 1	2001:DB8:ACAD:1::B	64	N/A
PC-A	NIC	2001:DB8:ACAD:1::3	64	FE80::1
PC-B	NIC	2001:DB8:ACAD:A::3	64	FE80::1

Objectives

Part 1: Set Up Topology and Configure Basic Router and Switch Settings

Part 2: Configure IPv6 Addresses Manually

Part 3: Verify End-to-End Connectivity

Background / Scenario

Knowledge of the Internet Protocol version 6 (IPv6) multicast groups can be helpful when assigning IPv6 addresses manually. Understanding how the all-router multicast group is assigned and how to control address assignments for the Solicited Nodes multicast group can prevent IPv6 routing issues and help ensure best practices are implemented.

In this lab, you will configure hosts and device interfaces with IPv6 addresses and explore how the all-router multicast group is assigned to a router. You will use **show** commands to view IPv6 unicast and multicast addresses. You will also verify end-to-end connectivity using the **ping** and **traceroute** commands.

Note: The routers used with CCNA hands-on labs are Cisco 1941 ISRs with Cisco IOS Release 15.2(4). The switches used are Cisco Catalyst 2960s with Cisco IOS Release 15.0(2). Other routers, switches and Cisco IOS versions can be used. Depending on the model and Cisco IOS version, the commands available and output produced might vary from what is shown in the labs. Refer to the Router Interface Summary table at the end of the lab for the correct interface identifiers.

Note: Make sure that the routers and switches have been erased and have no startup configurations. If you are unsure, contact your instructor.

Required Resources

- 1 Router (Cisco 1941 with Cisco IOS software, Release 15.2(4) or comparable)
- 1 Switch (Cisco 2960 with Cisco IOS Release 15.0(2) image or comparable)
- 2 PCs (Windows 7 or 8 with terminal emulation program, such as Tera Term)

- Console cables to configure the Cisco IOS devices via the console ports
- Ethernet cables as shown in the topology

Note: The Gigabit Ethernet interfaces on Cisco 1941 routers are autosensing and an Ethernet straight-through cable may be used between the router and PC-B. If using another model Cisco router, it may be necessary to use an Ethernet crossover cable.


Part 1: Set Up Topology and Configure Basic Router and Switch Settings

Step 1: Cable the network as shown in the topology.

Step 2: Initialize and reload the router and switch.

Step 3: Verify that the PC interfaces are configured to use the IPv6 protocol.

Verify that the IPv6 protocol is active on both PCs by ensuring that the **Internet Protocol Version 6 (TCP/IPv6)** check box is selected in the Local Area Connection Properties window.



Step 4: Configure the router.

- a. Console into the router and enable privileged EXEC mode.
- b. Assign the device name to the router.
- c. Disable DNS lookup to prevent the router from attempting to translate incorrectly entered commands as though they were hostnames.
- d. Assign **class** as the privileged EXEC encrypted password.

- e. Assign **cisco** as the console password and enable login.
- f. Assign **cisco** as the VTY password and enable login.
- g. Encrypt the clear text passwords.
- h. Create a banner that warns anyone accessing the device that unauthorized access is prohibited.
- i. Save the running configuration to the startup configuration file.

Step 5: Configure the switch.

- a. Console into the switch and enable privileged EXEC mode.
- b. Assign the device name to the switch.
- c. Disable DNS lookup to prevent the router from attempting to translate incorrectly entered commands as though they were hostnames.
- d. Assign **class** as the privileged EXEC encrypted password.
- e. Assign **cisco** as the console password and enable login.
- f. Assign **cisco** as the VTY password and enable login.
- g. Encrypt the clear text passwords.
- h. Create a banner that warns anyone accessing the device that unauthorized access is prohibited.
- i. Save the running configuration to the startup configuration file.

Part 2: Configure IPv6 Addresses Manually

Step 1: Assign the IPv6 addresses to Ethernet interfaces on R1.

- a. Assign the IPv6 global unicast addresses, listed in the Addressing Table, to both Ethernet interfaces on R1.
- b. Issue the **show ipv6 interface brief** command to verify that the correct IPv6 unicast address is assigned to each interface.

```
R1(config)# interface g0/0
R1(config-if)# ipv6 address 2001:db8:acad:a::1/64
R1(config-if)# no shutdown
R1(config-if)# interface g0/1
R1(config-if)# ipv6 address 2001:db8:acad:1::1/64
R1(config-if)# no shutdown
R1(config-if)# end
R1#
```

```
R1# show ipv6 interface brief
Em0/0                                [administratively down/down]
    unassigned
GigabitEthernet0/0                   [up/up]
    FE80::D68C:B5FF:FECE:A0C0
    2001:DB8:ACAD:A::1
GigabitEthernet0/1                   [up/up]
    FE80::D68C:B5FF:FECE:A0C1
    2001:DB8:ACAD:1::1
<output omitted>
```

- c. Issue the **show ipv6 interface g0/0** command. Notice that the interface is listing two Solicited Nodes multicast groups, because the IPv6 link-local (FE80) Interface ID was not manually configured to match the IPv6 unicast Interface ID.

Note: The link-local address displayed is based on EUI-64 addressing, which automatically uses the interface Media Access Control (MAC) address to create a 128-bit IPv6 link-local address.

```
R1# show ipv6 interface g0/0
GigabitEthernet0/0 is up, line protocol is up
  IPv6 is enabled, link-local address is FE80::D68C:B5FF:FECE:A0C0
  No Virtual link-local address(es):
  Global unicast address(es):
    2001:DB8:ACAD:A::1, subnet is 2001:DB8:ACAD:A::/64
  Joined group address(es):
    FF02::1
    FF02::1:FF00:1
    FF02::1:FFCE:A0C0
  MTU is 1500 bytes
<output omitted>
```

- d. To get the link-local address to match the unicast address on the interface, manually enter the link-local addresses on each of the Ethernet interfaces on R1.

```
R1# config t
Enter configuration commands, one per line. End with CNTL/Z.
R1(config)# interface g0/0
R1(config-if)# ipv6 address fe80::1 link-local
R1(config-if)# interface g0/1
R1(config-if)# ipv6 address fe80::1 link-local
R1(config-if)# end
R1#
```

Note: Each router interface belongs to a separate network. Packets with a link-local address never leave the local network; therefore, you can use the same link-local address on both interfaces.

- e. Re-issue the **show ipv6 interface g0/0** command. Notice that the link-local address has been changed to **FE80::1** and that there is only one Solicited Nodes multicast group listed.

```
R1# show ipv6 interface g0/0
GigabitEthernet0/0 is up, line protocol is up
  IPv6 is enabled, link-local address is FE80::1
  No Virtual link-local address(es):
  Global unicast address(es):
    2001:DB8:ACAD:A::1, subnet is 2001:DB8:ACAD:A::/64
  Joined group address(es):
    FF02::1
    FF02::1:FF00:1
  MTU is 1500 bytes
<output omitted>
```

What multicast groups have been assigned to interface G0/0?

Step 2: Enable IPv6 routing on R1.

- a. On a PC-B command prompt, enter the **ipconfig** command to examine IPv6 address information assigned to the PC interface.

Has an IPv6 unicast address been assigned to the network interface card (NIC) on PC-B? _____ **No**

- b. Enable IPv6 routing on R1 using the **IPv6 unicast-routing** command.

```
R1 # configure terminal
R1(config)# ipv6 unicast-routing
R1(config)# exit
R1#
*Dec 17 18:29:07.415: %SYS-5-CONFIG_I: Configured from console by console
```

- c. Use the **show ipv6 interface g0/0** command to see what multicast groups are assigned to interface G0/0. Notice that the all-router multicast group (FF02::2) now appears in the group list for interface G0/0.

Note: This will allow the PCs to obtain their IP address and default gateway information automatically using Stateless Address Autoconfiguration (SLAAC).

```
R1# show ipv6 interface g0/0
GigabitEthernet0/0 is up, line protocol is up
  IPv6 is enabled, link-local address is FE80::1
  No Virtual link-local address(es):
  Global unicast address(es):
    2001:DB8:ACAD:A::1, subnet is 2001:DB8:ACAD:A::/64 [EUI]
  Joined group address(es):
    FF02::1
    FF02::2
    FF02::1:FE00:1
  MTU is 1500 bytes
<output omitted>
```

- d. Now that R1 is part of the all-router multicast group, re-issue the **ipconfig** command on PC-B. Examine the IPv6 address information.

Why did PC-B receive the Global Routing Prefix and Subnet ID that you configured on R1?

Step 3: Assign IPv6 addresses to the management interface (SVI) on S1.

- a. Assign the IPv6 address listed in the Addressing Table to the management interface (VLAN 1) on S1. Also assign a link-local address for this interface. IPv6 command syntax is the same as on the router.

```
S1(config)# interface vlan 1
S1(config-if)# ipv6 address 2001:db8:acad:1::b/64
S1(config-if)# ipv6 address fe80::b link-local
S1(config-if)# end
S1#
*Mar 1 03:25:26.681: %SYS-5-CONFIG_I: Configured from console by console
```

- b. Verify that the IPv6 addresses are properly assigned to the management interface using the **show ipv6 interface vlan1** command.


```
S1# show ipv6 interface vlan1
```

```
Vlan1 is up, line protocol is up
IPv6 is enabled, link-local address is FE80::B
No Virtual link-local address(es):
Global unicast address(es):
  2001:DB8:ACAD:1::B, subnet is 2001:DB8:ACAD:1::/64
Joined group address(es):
  FF02::1
  FF02::1:FF00:B
MTU is 1500 bytes
ICMP error messages limited to one every 100 milliseconds
ICMP redirects are enabled
ICMP unreachable are sent
Output features: Check hwidb
ND DAD is enabled, number of DAD attempts: 1
ND reachable time is 30000 milliseconds (using 30000)
ND NS retransmit interval is 1000 milliseconds
S1#
```


Note: The default 2960 Switch Database Manager (SDM) template does not support IPv6. It may be necessary to issue the command **sdm prefer dual-ipv4-and-ipv6 default** to enable IPv6 addressing before applying an IPv6 address to the VLAN 1 SVI.

Step 4: Assign static IPv6 addresses to the PCs.

- Open the Local Area Connection Properties window on PC-A. Select **Internet Protocol Version 6 (TCP/IPv6)** and click **Properties**.



- Click the **Use the following IPv6 address** radio button. Refer to the Addressing Table and enter the **IPv6 address**, **Subnet prefix length**, and **Default gateway** information. Click **OK**.



- c. Click **Close** to close the Local Area Connection Properties window.
- d. Repeat Steps 4a to c to enter the static IPv6 information on PC-B. For the correct IPv6 address information, refer to the Addressing Table.
- e. Issue the **ipconfig** command from the command line on PC-B to verify the IPv6 address information.

Part 3: Verify End-to-End Connectivity

- a. From PC-A, ping **FE80::1**. This is the link-local address assigned to G0/1 on R1.

```
C:\>ping fe80::1

Pinging fe80::1 with 32 bytes of data:
Reply from fe80::1: time<1ms
Reply from fe80::1: time<1ms
Reply from fe80::1: time<1ms
Reply from fe80::1: time<1ms

Ping statistics for fe80::1:
    Packets: Sent = 4, Received = 4, Lost = 0 (0% loss),
    Approximate round trip times in milli-seconds:
        Minimum = 0ms, Maximum = 0ms, Average = 0ms

C:\>
```

Note: You can also test connectivity by using the global unicast address, instead of the link-local address.

- b. Ping the S1 management interface from PC-A.

```
C:\>ping 2001:db8:acad:1::b

Pinging 2001:db8:acad:1::b with 32 bytes of data:
Reply from 2001:db8:acad:1::b: time=14ms
Reply from 2001:db8:acad:1::b: time=2ms
Reply from 2001:db8:acad:1::b: time=2ms
Reply from 2001:db8:acad:1::b: time=3ms

Ping statistics for 2001:db8:acad:1::b:
    Packets: Sent = 4, Received = 4, Lost = 0 (0% loss),
    Approximate round trip times in milli-seconds:
        Minimum = 2ms, Maximum = 14ms, Average = 5ms

C:\>_
```

- c. Use the **tracert** command on PC-A to verify that you have end-to-end connectivity to PC-B.

```
C:\>tracert 2001:db8:acad:a::3

Tracing route to 2001:db8:acad:a::3 over a maximum of 30 hops
  1  <1 ms    <1 ms    <1 ms    2001:db8:acad:1::1
  2   5 ms    <1 ms    <1 ms    2001:db8:acad:a::3

Trace complete.

C:\>
```

- d. From PC-B, ping PC-A.

```
C:\>ping 2001:db8:acad:1::3

Pinging 2001:db8:acad:1::3 with 32 bytes of data:
Reply from 2001:db8:acad:1::3: time<1ms
Reply from 2001:db8:acad:1::3: time<1ms
Reply from 2001:db8:acad:1::3: time<1ms
Reply from 2001:db8:acad:1::3: time<1ms

Ping statistics for 2001:db8:acad:1::3:
    Packets: Sent = 4, Received = 4, Lost = 0 (0% loss),
    Approximate round trip times in milli-seconds:
        Minimum = 0ms, Maximum = 0ms, Average = 0ms

C:\>
```

- e. From PC-B, ping the link-local address for G0/0 on R1.

```
C:\>ping fe80::1

Pinging fe80::1 with 32 bytes of data:
Reply from fe80::1: time<1ms
Reply from fe80::1: time<1ms
Reply from fe80::1: time<1ms
Reply from fe80::1: time<1ms

Ping statistics for fe80::1:
    Packets: Sent = 4, Received = 4, Lost = 0 (0% loss),
    Approximate round trip times in milli-seconds:
        Minimum = 0ms, Maximum = 0ms, Average = 0ms

C:\>_
```

Note: If end-to-end connectivity is not established, troubleshoot your IPv6 address assignments to verify that you entered the addresses correctly on all devices.

Reflection

1. Why can the same link-local address, FE80::1, be assigned to both Ethernet interfaces on R1?

What is the Subnet ID of the IPv6 unicast address 2001:db8:acad::aaaa:1234/64?

Router Interface Summary Table

Router Interface Summary				
Router Model	Ethernet Interface #1	Ethernet Interface #2	Serial Interface #1	Serial Interface #2
1800	Fast Ethernet 0/0 (F0/0)	Fast Ethernet 0/1 (F0/1)	Serial 0/0/0 (S0/0/0)	Serial 0/0/1 (S0/0/1)
1900	Gigabit Ethernet 0/0 (G0/0)	Gigabit Ethernet 0/1 (G0/1)	Serial 0/0/0 (S0/0/0)	Serial 0/0/1 (S0/0/1)
2801	Fast Ethernet 0/0 (F0/0)	Fast Ethernet 0/1 (F0/1)	Serial 0/1/0 (S0/0/0)	Serial 0/1/1 (S0/0/1)
2811	Fast Ethernet 0/0 (F0/0)	Fast Ethernet 0/1 (F0/1)	Serial 0/0/0 (S0/0/0)	Serial 0/0/1 (S0/0/1)
2900	Gigabit Ethernet 0/0 (G0/0)	Gigabit Ethernet 0/1 (G0/1)	Serial 0/0/0 (S0/0/0)	Serial 0/0/1 (S0/0/1)

Note: To find out how the router is configured, look at the interfaces to identify the type of router and how many interfaces the router has. There is no way to effectively list all the combinations of configurations for each router class. This table includes identifiers for the possible combinations of Ethernet and Serial interfaces in the device. The table does not include any other type of interface, even though a specific router may contain one. An example of this might be an ISDN BRI interface. The string in parenthesis is the legal abbreviation that can be used in Cisco IOS commands to represent the interface.

Device Configs

Router R1 (After part 1 of this lab)

```
R1#sh run
Building configuration...

Current configuration : 1443 bytes
!
version 15.2
service timestamps debug datetime msec
service timestamps log datetime msec
service password-encryption
!
hostname R1
!
boot-start-marker
boot-end-marker
!
!
enable secret 4 06YFDUHH61wAE/kLkDq9BGho1QM5EnRtoyr8cHAUg.2
```

Lab - Configuring IPv6 Addresses on Network Devices

```
!  
no aaa new-model  
memory-size iomem 15  
!  
no ip domain lookup  
ip cef  
no ipv6 cef  
multilink bundle-name authenticated  
!  
!  
interface Embedded-Service-Engine0/0  
  no ip address  
  shutdown  
!  
interface GigabitEthernet0/0  
  no ip address  
  shutdown  
  duplex auto  
  speed auto  
!  
interface GigabitEthernet0/1  
  no ip address  
  shutdown  
  duplex auto  
  speed auto  
!  
interface Serial0/0/0  
  no ip address  
  shutdown  
  clock rate 2000000  
!  
interface Serial0/0/1  
  no ip address  
  shutdown  
!  
ip forward-protocol nd  
!  
no ip http server  
no ip http secure-server  
!  
control-plane  
!  
banner motd ^C  
*****  
* Warning: Unauthorized access is prohibited! *  
*****  
^C  
!  
line con 0
```

Lab - Configuring IPv6 Addresses on Network Devices

```
password 7 01100F175804
login
line aux 0
line 2
  no activation-character
  no exec
  transport preferred none
  transport input all
  transport output pad telnet rlogin lapb-ta mop udptn v120 ssh
  stopbits 1
line vty 0 4
  password 7 104D000A0618
  login
  transport input all
!
scheduler allocate 20000 1000
!
end
```

Switch S1 (After part 1 of this lab)

```
S1#sh run
Building configuration...

Current configuration : 1624 bytes
!
version 15.0
no service pad
service timestamps debug datetime msec
service timestamps log datetime msec
service password-encryption
!
hostname S1
!
boot-start-marker
boot-end-marker
!
enable secret 4 06YFDUHH61wAE/kLkDq9BGho1QM5EnRtoyr8cHAUg.2
!
no aaa new-model
system mtu routing 1500
!
!
no ip domain-lookup
!
spanning-tree mode pvst
spanning-tree extend system-id
!
vlan internal allocation policy ascending
!
```

```
interface FastEthernet0/1
shutdown
!
interface FastEthernet0/2
shutdown
!
interface FastEthernet0/3
shutdown
!
interface FastEthernet0/4
shutdown
!
interface FastEthernet0/5
!
interface FastEthernet0/6
!
interface FastEthernet0/7
!
interface FastEthernet0/8
!
interface FastEthernet0/9
!
interface FastEthernet0/10
!
interface FastEthernet0/11
!
interface FastEthernet0/12
!
interface FastEthernet0/13
!
interface FastEthernet0/14
!
interface FastEthernet0/15
!
interface FastEthernet0/16
!
interface FastEthernet0/17
!
interface FastEthernet0/18
!
interface FastEthernet0/19
!
interface FastEthernet0/20
!
interface FastEthernet0/21
!
interface FastEthernet0/22
!
interface FastEthernet0/23
```

Lab - Configuring IPv6 Addresses on Network Devices

```
!  
interface FastEthernet0/24  
!  
interface GigabitEthernet0/1  
!  
interface GigabitEthernet0/2  
!  
interface Vlan1  
no ip address  
!  
ip http server  
ip http secure-server  
!  
banner motd ^C  
*****  
* Warning: Unauthorized access is prohibited! *  
*****  
^C  
!  
line con 0  
password 7 121A0C041104  
login  
line vty 0 4  
password 7 121A0C041104  
login  
line vty 5 15  
password 7 121A0C041104  
login  
!  
end
```

Router R1 (Final)

```
R1#show run  
Building configuration...  
  
Current configuration : 1577 bytes  
!  
version 15.2  
service timestamps debug datetime msec  
service timestamps log datetime msec  
service password-encryption  
!  
hostname R1  
!  
boot-start-marker  
boot-end-marker  
!  
enable secret 4 06YFDUHH61wAE/kLkDq9BGho1QM5EnRtoyr8cHAUg.2  
!
```

Lab - Configuring IPv6 Addresses on Network Devices

```
no aaa new-model
memory-size iomem 15
!
no ip domain lookup
ip cef
ipv6 unicast-routing
ipv6 cef
multilink bundle-name authenticated
!
!
interface Embedded-Service-Engine0/0
 no ip address
 shutdown
!
interface GigabitEthernet0/0
 no ip address
 duplex auto
 speed auto
 ipv6 address FE80::1 link-local
 ipv6 address 2001:DB8:ACAD:A::1/64
!
interface GigabitEthernet0/1
 no ip address
 duplex auto
 speed auto
 ipv6 address FE80::1 link-local
 ipv6 address 2001:DB8:ACAD:1::1/64
!
interface Serial0/0/0
 no ip address
 shutdown
 clock rate 2000000
!
interface Serial0/0/1
 no ip address
 shutdown
!
ip forward-protocol nd
!
no ip http server
no ip http secure-server
!
control-plane
!
banner motd ^C
*****
* Warning: Unauthorized access is prohibited! *
*****
^C
```

```
!  
line con 0  
  password 7 01100F175804  
  login  
line aux 0  
line 2  
  no activation-character  
  no exec  
  transport preferred none  
  transport input all  
  transport output pad telnet rlogin lapb-ta mop udptn v120 ssh  
  stopbits 1  
line vty 0 4  
  password 7 104D000A0618  
  login  
  transport input all  
!  
scheduler allocate 20000 1000  
!  
end
```

Switch S1 (Final)

```
S1#sh run
```

```
Building configuration...
```

```
Current configuration : 1733 bytes
```

```
!  
!  
version 15.0  
no service pad  
service timestamps debug datetime msec  
service timestamps log datetime msec  
service password-encryption  
!  
hostname S1  
!  
boot-start-marker  
boot-end-marker  
!  
enable secret 4 06YFDUHH61wAE/kLkDq9BGho1QM5EnRtoyr8cHAUg.2  
!  
no aaa new-model  
system mtu routing 1500  
!  
no ip domain-lookup  
!  
spanning-tree mode pvst
```

```
spanning-tree extend system-id
!
vlan internal allocation policy ascending
!
interface FastEthernet0/1
shutdown
!
interface FastEthernet0/2
shutdown
!
interface FastEthernet0/3
shutdown
!
interface FastEthernet0/4
shutdown
!
interface FastEthernet0/5
!
interface FastEthernet0/6
!
interface FastEthernet0/7
!
interface FastEthernet0/8
!
interface FastEthernet0/9
!
interface FastEthernet0/10
!
interface FastEthernet0/11
!
interface FastEthernet0/12
!
interface FastEthernet0/13
!
interface FastEthernet0/14
!
interface FastEthernet0/15
!
interface FastEthernet0/16
!
interface FastEthernet0/17
!
interface FastEthernet0/18
!
interface FastEthernet0/19
```


Lab - Configuring IPv6 Addresses on Network Devices

```
!  
interface FastEthernet0/20  
!  
interface FastEthernet0/21  
!  
interface FastEthernet0/22  
!  
interface FastEthernet0/23  
!  
interface FastEthernet0/24  
!  
interface GigabitEthernet0/1  
!  
interface GigabitEthernet0/2  
!  
interface Vlan1  
  no ip address  
  ipv6 address FE80::B link-local  
  ipv6 address 2001:DB8:ACAD:1::B/64  
!  
ip http server  
ip http secure-server  
!  
!  
banner motd ^C  
*****  
* Warning: Unauthorized access is prohibited! *  
*****  
^C  
!  
line con 0  
  password 7 121A0C041104  
  login  
line vty 0 4  
  password 7 121A0C041104  
  login  
line vty 5 15  
  password 7 121A0C041104  
  login  
!  
end
```